

Fixed Coaxial Attenuators

Model 90

Medium Power, N & 3.5mm Connectors Bi-directional Design

dc to 18.0 GHz 50 Watts







Features

- // Precision injection molded connectors.
- // Designed to meet environmental requirements of MIL-DTL-3933.
- // Flat Response.
- // Low Intermodulation option available.

Specifications

NOMINAL IMPEDANCE: 50 Ω

FREQUENCY RANGE: dc to 18.0 GHz

MAXIMUM DEVIATION OVER FREQUENCY:						
Nominal	Deviation (dB)					
ATTN (dB)	90	90-LIM				
3, 6	<u>+</u> 1.0					
10, 20, 30	<u>+</u> 1.0	+2.0 / -1.0				

MAXIMUM SWR:	
Frequency (GHz)	SWR
dc - 8 8 - 12.4 12.4 - 18	1.15 1.20 1.30
12.4 - 10	1.30

3rd ORDER INTERMODULATION (90-XX-XX-LIM ONLY):

Reflected Levels (IM3), -100 dBc and Through Levels (IM3), -110 dBc with two input signals @ 869 MHz and 891 MHz with average carrier power levels of +43 dBm each. Option only available 10, 20, 30 dB.

POWER RATING (mounted horizontally): 50 watts **average (bi-directional)** to 25°C ambient temperature, derated linearly to 5 Watts @ 125°C. 1 kW **peak** (5 μsec pulse width; 2.5% duty cycle).

POWER COEFFICIENT: <0.0003 dB/dB/watt
TEMPERATURE COEFFICIENT: <0.0004 dB/dB/°C

TEMPERATURE RANGE: -55 °C to 125 °C

TEST DATA: Swept data plots of attenuation and SWR from 50 MHz to 18 GHz. Frequency markers at 0.05, 2.0, 4.0, 8.0, 12.4, 18.0 GHz

CONNECTORS: Type N connectors per MIL-STD-348 interface dimensions - mate nondestructively with MIL-C-39012 connectors.


3.5mm Connectors - mate nondestructively with SMA per MIL-C-39012, 2.92mm and 3.5mm connectors.

<u>Options</u>	<u>Description</u>	<u>Options</u>	Description
1	3.5mm Female	3	Type N, Female
2	3.5mm Male	4	Type N, Male

CONSTRUCTION: Black, finned aluminum body, gold plated beryllium copper contacts.

WEIGHT: 120 g (4.2 oz.) maximum

PHYSICAL DIMENSIONS:




Connector	DIM A	Connector	DIM A
N Male	24.1 (0.95)	3.5mm Male	14.0 (0.55)
N Female	19.0 (0.75)	3.5mm Female	13.2 (0.52)

NOTE: All dimensions are given in mm (inches) and are maximum, unless otherwise specified.

MODEL NUMBER DESCRIPTION:

Example:



^{*} Unit is bi-directional & full power may be applied to either J1 or J2.

^{**}Add -LIM to entire model number for Low Intermodulation option. Option only available in 10, 20, 30 dB.