TERMINATION REVERSE POLARITY SMA MALE

DC - 6 GHz 1 WATT



MODELS: 3206-SMARP

SPECIFICATIONS:

Electrical:

Frequency Range ______ DC - 6 GHz VSWR

DC - 3 GHz _______ 1.15:1 Max.
3 - 6 GHz _______ 1.20:1 Max.

Impedance ______ 50 Ohms
Input Power ______ 1 Watt Avg. @ +25°C


Derated Linearly to 10% @ +125°C

Operating Temperature Range _____ -55°C to +125°C

Mechanical:

Reverse Polarity SMA Male __ White Bronze Plated Brass Mates with Reverse Polarity SMA Female Conductor ____ Gold Plated Beryllium Copper Coupling Nut ____ White Bronze Plated Brass

Model Number: 3206-SMARP



Note:

Unit Shown, and Dimensions Occur, with Coupling Jut

Biased Fully Forward (as Installed).

Note: Dimensions in Brackets are Expressed in Millimeters and are for Reference Only.

Design specifications are subject to change without notice.

Contact factory for technical specifications before purchasing or use.

3206—SMARP; REV—
300 Dino Drive • Ann Arbor, MI 48103—9457 U.S.A. • 888—244—6638 or 734—426—5553 • FAX 734—426—5557 • inmet.apitech.com